

HP ProLiant DL385 SCSI Cabling Matrix			
Server Specifics			
Server	Integrated Array Controller	Ports	Optional SCSI Controllers/HBAs Supported
DL385	Smart Array 6i	(2) Internal	Smart Array 64x(x) Ultra320 SCSI HBA
Internal Storage Options			
Ultra320 Hot-Plug Hard Drives	No cables are required if connecting to the integrated Smart Array 6i. The SCSI Configuration Kit (PN 364471-B21) is required if connecting to a Smart Array controller or Ultra320 HBA in a slot. SCSI Configuration Kit (PN 364471-B21) includes 2 long SCSI cables and a SCSI terminator card used to split the drive backplane.		
DAT hot-plug tape drives			
External Storage Options			
To connect anything externally, an Ultra320 SCSI controller or Smart Array controller must be added to the system.			
Direct Attached	SCSI Connector on Option	Cable Included with Storage Option?	
MSA 20	VHDCI	Yes, VHDCI-VHDCI 3 ft	
MSA 30	VHDCI		
MSA 500	VHDCI	Yes, VHDCI-VHDCI 6 ft	
Tape/Optical	SCSI Connector on Option	Cable Included with Storage Option?	
DAT 40e	LVD Wide 68-pin		
DAT 72e	LVD Wide 68-pin		
Ultrium 215e	LVD Wide 68-pin		
Ultrium 230e	LVD Wide 68-pin	Yes, HD68-VHDCI	
Ultrium 460e	LVD Wide 68-pin		
DLT VS 80e	LVD Wide 68-pin		
SDLT 320e	LVD Wide 68-pin		
Tape Autoloaders	SCSI Connector on Option	Cable Included with Storage Option?	
1/8 Ultrium 230	LVD Wide 68-pin		
1/8 Ultrium 460	LVD Wide 68-pin		
1/8 DLT VS 80	LVD Wide 68-pin		
SSL1016 Ultrium 230	LVD Wide 68-pin	Yes, HD68-VHDCI 1.5 m	
SSL1016 Ultrium 460	LVD Wide 68-pin		
SSL1016 DLT1	LVD Wide 68-pin		
DAT 40x6	LVD Wide 68-pin		
DAT 72x6	LVD Wide 68-pin		
Tape Libraries	SCSI Connector on Option	Cable Included with Storage Option?	
MSL6030	VHDCI		
MSL6060	VHDCI		
MSL5026S2	VHDCI	No, order one of the following VHDCI-VHDCI cables	
MSL5052S2	VHDCI	341175-B21 - 12-ft VHDCI-VHDCI cable	
MSL5030	VHDCI	341174-B21 - 6-ft VHDCI-VHDCI cable	
MSL5060	VHDCI		
ESL9595	VHDCI		
ESL9000	VHDCI		
Optical Jukeboxes	SCSI Connector on Option	Cable Included with Storage Option?	
300mx	LVD Wide 68-pin	No, order one of the following HD68-VHDCI cables	
600mx	LVD Wide 68-pin	341177-B21 - 12-ft VHDCI-HD68 cable	
700mx	LVD Wide 68-pin	341176-B21 - 6-ft VHDCI-HD68 cable	
1200mx	LVD Wide 68-pin	201160-B21 - 10-mm VHDCI-HD68 cable	
2200mx	LVD Wide 68-pin		
NOTE: The information in this matrix lists whether or not additional cables need to be purchased with controller-to-option configuration. For information on how to cable an option, refer to the <i>HP ProLiant DL385 Server User Guide</i> and the device-specific documentation. For information on the specific options supported by the server, refer to the server and device QuickSpecs.			
© 2002, 2005 Hewlett-Packard Development Company, L.P.			
Hewlett-Packard Company shall not be liable for technical or editorial errors or omissions contained herein. The information in this document is provided "as is" without warranty of any kind and is subject to change without notice. The information contained herein is subject to change without notice. The only warranties for HP products and services are set forth in the express warranty statements accompanying such products and services. Nothing herein should be construed as constituting an additional warranty. HP shall not be liable for technical or editorial errors or omissions contained herein.			